

INSTRUCTIONS

Daisy Chain Wafer Downlight FA

RAB®

RAB Lighting is committed to creating high-quality, affordable, well-designed and energy-efficient LED lighting and controls that make it easy for electricians to install and end users to save energy. We'd love to hear your comments. Please call the Marketing Department at 888-RAB-1000 or email: marketing@rablighting.com

DAISY4
DAISY4B
DAISY6
DAISY6B



IMPORTANT

READ CAREFULLY BEFORE INSTALLING FIXTURE. RETAIN THESE INSTRUCTIONS FOR FUTURE REFERENCE.

RAB fixture must be wired in accordance with the National Electrical Code and all applicable local codes. Proper grounding is required for safety. THIS PRODUCT MUST BE INSTALLED IN ACCORDANCE WITH THE APPLICABLE INSTALLATION CODE BY A PERSON FAMILIAR WITH THE CONSTRUCTION AND OPERATION OF THE PRODUCT AND THE HAZARDS INVOLVED.


TO PREVENT ELECTRICAL SHOCK, POWER SHOULD BE TURNED OFF AT THE FUSE BOX BEFORE INSTALLATION.

SAFETY WARNINGS:

Read all product labels and directions.

- **WARNING – Risk of fire or electric shock.** Install this kit only in the luminaires that have the construction features and dimensions shown in the photographs and/or drawings and where the input rating of the retrofit kit does not exceed the input rating of the luminaire.
- Installation should be performed only by a qualified electrician in accordance with the National Electrical Code and relevant local codes. Do not make or alter any open holes in an enclosure of wiring or electrical components during kit installation.
- **WARNING – To prevent wiring damage or abrasion, do not expose wiring to edges of sheet metal or other sharp objects.**
- **INSTALLATION SHOULD ONLY BE PERFORMED AFTER POWER TO THE FIXTURE HAS BEEN DISCONNECTED.**
- These instructions shall be included on an information sheet packaged with each unit.
- Against using the luminaire with other than a Listed Class 2 Power Unit.
- This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

WHAT'S IN THE BOX




Fixture (1)




Cable Connector(1)



Template (1)



DLPLATE/WFR3468/NB
Mounting plate with nailer bar



DLPLATE/WFR3456
Mounting plate

TOOLS NEEDED

This Daisy Chain Wafer requires very few tools for installation. A screwdriver and a pair of wirecutters will help to install.

INSTRUCTIONS

Daisy Chain Wafer Downlight FA




RAB Lighting is committed to creating high-quality, affordable, well-designed and energy-efficient LED lighting and controls that make it easy for electricians to install and end users to save energy. We'd love to hear your comments. Please call the Marketing Department at 888-RAB-1000 or email: marketing@rablighting.com

INSTALLATION INTRODUCTION


1. Turn power OFF from the electrical panel before installation.
2. Carefully measure where fixture will be installed, use template inside box to cut hole in ceiling. (Fig.1)

Fig: 1




3. Separate connector, cable, and fixture. (Fig.2)

Fig: 2




4. Separate the connector by rotating the bottom piece counterclockwise. (Fig.3)

Fig: 3




5. Slide either edge of the cable into the slot of the connector's top. (Fig.4)

Fig: 4



6. Allow the fixture to hang freely, align the metal pin on the bottom piece (attached to the light) with the metal insert in the top. (Fig.5)


Fig: 5



INSTALLATION INTRODUCTION (cont'd)


7. Push together and rotate the bottom piece clockwise onto the top, until secure. (Fig.6)

Fig: 6




8. Select desired CCT. (Fig.7)

Fig: 7




9. Connect the fixture to the connector. (Fig.8)

Fig: 8



10. Lift both retention tabs upward. Push until the trim sits flush against the ceiling. (Fig.9)

Fig: 9



IMPORTANT NOTE:

Must be installed with Model No. DAISYKIT4, DAISYKIT6, DAISYKIT4B, DAISYKIT6B. Maximum connected wafer is 10 pcs (4-inch) and 8 pcs (6-inch). For details see instructions for DAISYKITXX.

Note: These instructions do not cover all details or variations in equipment nor do they provide for every possible situation during installation, operation or maintenance.