

RAB®

X22-20 @ 20W	3000K			4000K			5000K		
BEAM SETTING	90°	75°	55°	90°	75°	55°	90°	75°	55°
BEAM ANGLE	93°	77°	57°	93°	77°	57°	93°	77°	57°
NEMA TYPE	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V
INPUT WATTS	21W	21W	20.9W	20.1W	20W	20W	20.7W	20.7W	20.7W
LUMENS	2,908	2,831	2,570	3,120	3,039	2,767	3,060	2,978	2,722
EFFICACY	138.5	134.8	123.0	155.2	152.0	138.4	147.8	143.9	131.5
CRI	81	82	82	84	83	83	82	82	82
VOLTAGE RATINGS	120-277V								

X22-20 @ 17W	3000K			4000K			5000K		
BEAM SETTING	90°	75°	55°	90°	75°	55°	90°	75°	55°
BEAM ANGLE	93°	77°	57°	93°	77°	57°	93°	77°	57°
NEMA TYPE	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V
INPUT WATTS	16.8W	18.2W	16.8W	16.1W	16W	16.1W	16.6W	16.6W	16.6W
LUMENS	2,385	2,547	2,324	2,559	2,495	2,298	2,510	2,700	2,260
EFFICACY	142	140.5	138.3	158.9	155.9	142.7	151.2	148.9	136.1
CRI	81	82	82	84	83	83	82	83	82
VOLTAGE RATINGS	120-277V								

X22-20 @ 13W	3000K			4000K			5000K		
BEAM SETTING	90°	75°	55°	90°	75°	55°	90°	75°	55°
BEAM ANGLE	93°	77°	57°	93°	77°	57°	93°	77°	57°
NEMA TYPE	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V
INPUT WATTS	13W	12.9W	13W	12.4W	12.3W	12.4W	12.8W	12.7W	12.9W
LUMENS	1,891	1,847	1,679	2,029	1,983	1,808	1,990	1,943	1,778
EFFICACY	145.5	143.2	129.2	163.6	161.2	145.8	155.5	153.0	137.8
CRI	82	81	82	84	83	83	82	82	82
VOLTAGE RATINGS	120-277V								

X22-20 @ 10W	3000K			4000K			5000K		
BEAM SETTING	90°	75°	55°	90°	75°	55°	90°	75°	55°
BEAM ANGLE	93°	77°	57°	93°	77°	57°	93°	77°	57°
NEMA TYPE	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V	7H X 6V	6H X 6V	6H X 6V
INPUT WATTS	9.9W	10W	10W	9.6W	9.5W	9.6W	10W	9.9W	9.9W
LUMENS	1,551	1,441	1,310	1,581	1,547	1,410	1,474	1,723	1,516
EFFICACY	156.7	144.1	131.0	164.7	162.8	146.9	147.4	159	153.1
CRI	82	82	81	84	83	83	82	83	82
VOLTAGE RATINGS	120-277V								