

# Ballast Compatibility List



## T8 LED 4ft.

T8-12-48G-830-DIR  
 T8-12-48G-835-DIR  
 T8-12-48G-840-DIR  
 T8-12-48G-850-DIR  
 T8-15-48G-830-DIR  
 T8-15-48G-835-DIR

T8-15-48G-840-DIR  
 T8-15-48G-850-DIR  
 T8-12-48P-830-DIR  
 T8-12-48P-835-DIR  
 T8-12-48P-840-DIR  
 T8-12-48P-850-DIR

T8-15-48P-830-DIR  
 T8-15-48P-835-DIR  
 T8-15-48P-840-DIR  
 T8-15-48P-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
Philips-Advance	ICN-3P32-N	IS	3	Parallel	✓	✓	✓	✓
	ICN-2P32-N	IS	3	Parallel	✓	✓	✓	✓
	ICN-132-MC	IS	1	Parallel	✓	✓	N/A	N/A
	IOP-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	ICN-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	ICN-1P32-N	IS	1	Parallel	✓	✓	N/A	N/A
	IOPA-4P32-N	IS	4	Parallel	✓	✓	✓	✓
	IOPA-3P32-LW-N	IS	2	Parallel	✓	✓	✓	✓
	REB-4P32-SC	IS	4	Parallel	✓	N/A	✓	N/A
	IOP-2P32-LW-N	IS	2	Parallel	✓	✓	✓	✓
	IOP-1P32-LW-N	IS	1	Parallel	✓	✓	N/A	N/A
	GOPA-2P32-N	IS	2	Parallel	✓	✓	✓	✓
	IOPA-2P32-LW-N	IS	2	Parallel	✓	✓	✓	✓
	IOP-3P32-LW-SC	IS	3	Parallel	✓	✓	✓	✓
	IOPA-3P32-N	IS	3	Parallel	✓	✓	✓	✓
	ICN-2P16-TLED-N	IS	2	Parallel	✓	✓	✓	✓
ICN-4P16-TLED-N	IS	4	Parallel	✓	✓	✓	✓	
General Electric	GE332MAX-G-N	IS	3	Parallel	✓	✓	✓	✓
	GE432MAX-G-N	IS	4	Parallel	✓	✓	✓	✓
	GE232MAX-G-N	IS	2	Parallel	✓	✓	✓	✓
	GE132MAXP-N/ULTRA	IS	1	Parallel	✓	✓	N/A	N/A
	GE432MAX-G-L	IS	4	Parallel	✓	✓	✓	✓
	GE332MAX-G-L	IS	3	Parallel	✓	✓	✓	✓
	GE432MAX-N/ULTRA	IS	4	Parallel	✓	✓	✓	✓
	GE232MAX-G-L	IS	2	Parallel	✓	✓	✓	✓
	GE332MAX-L/ULTRA	IS	3	Parallel	✓	✓	✓	✓
	GE232MAXP-N/ULTRA	IS	2	Parallel	✓	✓	✓	✓
	GE132MAX-L/ULTRA	IS	1	Parallel	✓	✓	N/A	N/A
	GE232-MV-N	IS	2	Parallel	✓	✓	✓	✓
	GE332-MV-N	IS	3	Parallel	✓	✓	✓	✓

# Ballast Compatibility List



## T8 LED 4ft.

T8-12-48G-830-DIR  
 T8-12-48G-835-DIR  
 T8-12-48G-840-DIR  
 T8-12-48G-850-DIR  
 T8-15-48G-830-DIR  
 T8-15-48G-835-DIR

T8-15-48G-840-DIR  
 T8-15-48G-850-DIR  
 T8-12-48P-830-DIR  
 T8-12-48P-835-DIR  
 T8-12-48P-840-DIR  
 T8-12-48P-850-DIR

T8-15-48P-830-DIR  
 T8-15-48P-835-DIR  
 T8-15-48P-840-DIR  
 T8-15-48P-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
OSRAM SYLVANIA	QHE 1X32T8/UNV PSN-MC	IS	1	Parallel	✓	✓	N/A	N/A
	QHE 2X32T8/UNV ISN-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISN-SC	IS	3	Parallel	✓	✓	✓	✓
	QHE 4X32T8/UNV ISN-SC	IS	4	Parallel	✓	✓	✓	✓
	QHE 3X32T8/UNV ISL-SC	IS	3	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV ISL-SC	IS	2	Parallel	✓	✓	✓	✓
	QHE 2X32T8/UNV PSN-MC	PRS	2	Parallel	✓	✓	✓	✓
	QTP 4X32T8/UNV ISN-SC	IS	4	Parallel	✓	✓	✓	✓
	QTP 3X32T8/UNV ISN-SC	IS	3	Parallel	✓	✓	✓	✓
	QTP 2X32T8/UNV ISN-SC	IS	2	Parallel	✓	✓	✓	✓
	QTP 2x32T8/277 ISN-D	IS	2	Parallel	✓	✓	✓	✓
Sunlite	40155-SU.SB/232/MV	IS	2	Parallel	✓	✓	✓	✓
Plusrite	BAF232IS/MV/L	IS	2	Parallel	✓	✓	✓	✓
	BAF332IS/MV/L	IS	3	Parallel	✓	✓	✓	✓
	BAF232IS/MV	IS	2	Parallel	✓	✓	✓	✓
VANTAGE	VE132120HLP	IS	1	Parallel	✓	N/A	N/A	N/A
Fulham-WORK HORSE	WHSG4-UNV-T8-IS	IS	4	Parallel	✓	✓	✓	✓
Universal Lighting Technologies	B132IUNVHP-N	IS	1	Parallel	✓	✓	N/A	N/A
	B332IUNVEL-A	IS	3	Parallel	✓	✓	✓	✓
	B232I120RES-A	IS	2	Parallel	✓	N/A	✓	N/A
	B232IUNVHP-B	IS	2	Parallel	✓	✓	✓	✓
	B432IUNVHE-A	IS	4	Parallel	✓	✓	✓	✓
	B332PUNVHE-A	PS	3	Parallel	✓	✓	✓	✓
	B232IUNVHP-N	IS	2	Parallel	✓	✓	✓	✓
	B232IUNVEL-A	IS	2	Parallel	✓	✓	✓	✓
Halco	EP432IS/MV/HE	IS	4	Parallel	✓	✓	✓	✓
	EP332IS/MV/HE	IS	3	Parallel	✓	✓	✓	✓
Triad	B332IUNVHP-A	IS	3	Parallel	✓	✓	✓	✓

# Ballast Compatibility List



## T8 LED 4ft.

T8-12-48G-830-DIR  
 T8-12-48G-835-DIR  
 T8-12-48G-840-DIR  
 T8-12-48G-850-DIR  
 T8-15-48G-830-DIR  
 T8-15-48G-835-DIR

T8-15-48G-840-DIR  
 T8-15-48G-850-DIR  
 T8-12-48P-830-DIR  
 T8-12-48P-835-DIR  
 T8-12-48P-840-DIR  
 T8-12-48P-850-DIR

T8-15-48P-830-DIR  
 T8-15-48P-835-DIR  
 T8-15-48P-840-DIR  
 T8-15-48P-850-DIR

Brand	Part Number	Starting Method	Number of Lamps	Lamp Connection	Nominal Lamp Load		Reduced Lamp Load	
					Input Voltage 120	Input Voltage 277	Input Voltage 120	Input Voltage 277
DAMAR	EL232HL-120/277HF(1688D)	IS	2	Parallel	✓	✓	✓	✓
MAXLITE	MLEU322HEL/SC	IS	2	Parallel	✓	✓	✓	✓
HOWARD INDUSTRIES	EP4/32IS/MV/MC/HE	IS	4	Parallel	✓	✓	✓	✓
	EPL4/32IS/MV/MC/HE	IS	4	Parallel	✓	✓	✓	✓
	EP3/32IS/MV/MC/HE	IS	3	Parallel	✓	✓	✓	✓
	EPL2/32IS/MV/MC/HE	IS	2	Parallel	✓	✓	✓	✓
KEYSTONE	KTEB-232-UV-IS-L-P	IS	2	Parallel	✓	✓	✓	✓
	KTEB-432-UV-IS-N-P	IS	4	Parallel	✓	✓	✓	✓
	KTEB-232-UV-IS-N-P	IS	2	Parallel	✓	✓	✓	✓
	KTEB-332-UV-IS-N-P	IS	3	Parallel	✓	✓	✓	✓
ESPEN	VE232MVHIPE	IS	2	Parallel	✓	✓	✓	✓
	VE232MVHIPLE	IS	2	Parallel	✓	✓	✓	✓
	VE2P32MVHIPE	IS	2	Parallel	✓	✓	✓	✓
	VE4P32MVHIPE	IS	4	Parallel	✓	✓	✓	✓
Watran	DB-232N-MV-TP-HE	IS	2	Parallel	✓	✓	✓	✓
EIKO	PM-2X32T8-UNV-IS-L	IS	2	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS-L	IS	3	Parallel	✓	✓	✓	✓
	PM-3X32T8-UNV-IS	IS	3	Parallel	✓	✓	✓	✓
ARCATA	ACT 3P32ISUNVLE	IS	3	Parallel	✓	✓	✓	✓
TCP	TCP3P32ISUNVH	IS	3	Parallel	✓	✓	✓	✓
	E4P32ISUNVE	IS	4	Parallel	✓	✓	✓	✓
Cooper Lighting	CL-432ISUNV-R1-B	IS	4	Parallel	✓	✓	✓	✓
ProLume	EP232IS/L/MV/SL	IS	2	Parallel	✓	✓	✓	✓